


[Investor Relations](#)

[\[change\]](#)
[Contact](#)





[HOME](#)
[PRODUCTS](#)
[SERVICES](#)
[SHOWCASE](#)
[NEWS & IR](#)
[ABOUT RITAR](#)
[Products>>>RA Series](#)


### AGM BATTERIES

- » RT Series
- » RA Series
- » RL Series
- » DC Series
- » EV Series
- » FT Series
- » HR Series

### GEL BATTERIES

- » RT Series
- » RA Series
- » RL Series
- » DC Series
- » FT Series

### CHARGERS

- » Electric Bicycle/Golf Charger Series
- » Solar Charger Series

### SWITCH POWER SUPPLY

- » Wall Type
- » Desktop Type



### AGM BATTERIES>>>RA Series

#### ※ General Features

##### Higher Reliability and Quality

Throughout the whole manufacturing process, PPM and ISO 9001 are carried out to make sure that the product reliability and defect ratio meet with the PPM standard.

##### Higher Power Density

A special assembly technology is used to enhance power density to a considerable level.

##### Reliable Construction

The extra strong construction ABS container reduces case bulging and plate warping, ensuring long life and high performance.

##### Valve regulating

Perfect venting system, which operates under low pressure, is designed to release excess gas and keep the internal pressure within the optimum range of safe and efficient performance.

##### Excellent Recovery from Deep Discharge

Unique technical processes are used into the grid alloy and electrolyte additives, so that the battery can be recharged easily to a normal level even after being over-discharged.

Model	Voltage	Capacity			Dimension				Weight	Terminal	Maximum Discharge Current	Maximum Charge Current	Internal Resistance
		1hr	3hr	10hr	Length	Width	Height	TotalHeight					
<a href="#">RA6-100</a>	6			100	194	170	205	210	16.5	F14	1000	30.0	2.0
<a href="#">RA6-150</a>	6			150	260	180	247	250	23.5	F12	1500	45.0	2.0
<a href="#">RA6-200</a>	6			200	322	177.5	226	247	30.0	F14/F16	2000	60.0	4.0
<a href="#">RA6-225</a>	6			225	322	177.5	226	247	32.0	F14/F16	2250	67.5	4.0
<a href="#">RA12-33</a>	12			33	195	130	159	--	10.2	F7/F11	330	9.9	9.0
<a href="#">RA12-40</a>	12			40	198	166	171	171	13.2	F4/F11	400	12.0	8.0
<a href="#">RA12-45</a>	12			45	198	166	171	171	14.0	F4/F11	450	13.5	8.0
<a href="#">RA12-55</a>	12			55	229	138	210	235	18.0	F11/F15	550	16.5	6.0
<a href="#">RA12-60</a>	12			60	260	169	210	235	20.5	F15	600	18.0	6.0
<a href="#">RA12-65</a>	12			65	350	167	179	182	21.0	F5/F11	325	19.5	6.0
<a href="#">RA12-70</a>	12			70	350	167	179	182	22.5	F5/F11	700	21.0	6.0
<a href="#">RA12-70S</a>	12			70	260	169	210	235	21.5	F11/F15	700	21.0	6.0
<a href="#">RA12-75</a>	12			75	260	169	210	235	23.5	F11/F15	750	22.5	6.0
<a href="#">RA12-80</a>	12			80	350	167	179	182	24.0	F5/F11	800	24.0	5.5
<a href="#">RA12-90</a>	12			90	306.5	168.5	211	235	28.5	F11/F15	900	27.0	5.2
<a href="#">RA12-100</a>	12			100	328	172	222	222	30.0	F5/F12	1000	30.0	5.0
<a href="#">RA12-100S</a>	12			100	306.5	168.5	210	235	29.0	F12/F15	1000	30.0	4.8
<a href="#">RA12-120</a>	12			120	407	177	225	225	35.5	F5/F12	1200	36.0	4.5
<a href="#">RA12-120S</a>	12			120	328	177	222	222	32.0	F5/F12	1200	36.0	4.0
<a href="#">RA12-134</a>	12			134	340	173	280	285	41.5	F5/F12	1340	40.2	4.5

<a href="#">RA12-145</a>	12	145	340	173	280	285	44.0	F5/F12	1450	43.5	4.5
<a href="#">RA12-160</a>	12	160	530	209	214	214	53.0	F16/F12	1600	48.0	4.5
<a href="#">RA12-150</a>	12	150	483	170	240	240	44.5	F5/F12	1500	45.0	4.0
<a href="#">RA12-200</a>	12	200	522	240	219	240	60.0	F12/F16	2000	60.0	4.0
<a href="#">RA12-225</a>	12	225	522	240	219	240	65.0	F12/F16	2250	67.5	3.8
<a href="#">RA12-240</a>	12	240	522	240	219	240	69.0	F12/F16	2400	72.0	3.8
<a href="#">RA12-260</a>	12	260	520	268	220	225	74	F14	2600	78.0	3.5

**\* Main Application**

Communication equipment;  
 Fire & security systems;  
 Uninterruptible power supplies;  
 Telecommunication systems;  
 Electronic cash registers;  
 Electronic test equipment;  
 Recessor based office machines;  
 Control equipment;  
 Electric powered bicycle and wheelchairs;  
 Geophysical equipment;  
 Marine equipment;  
 Medical equipment;  
 Portable cine & video lights;  
 Power tools Solar powered systems;  
 Television & video recorders;  
 Vending machines;  
 Other standby or primary power supplies.